

CAUTION: EXTERNAL ILLUMINATION SOURCE REQUIRED
IMPORTANT SAFEGUARDS. READ AND FOLLOW
ALL SAFETY INSTRUCTIONS.

Minimal external illumination - 5 foot candles (54 lux) of light.

- The sign should be charged for a minimum 60 minutes to obtain full operation conditions.
- The sign should be mounted in a manner that ensures rigidity and mechanical sufficiency.
- External illumination source must be reliable and supplied by a circuit not controlled by automatic timers or sensors and whose controls are accessible only to authorized personnel.
- External illumination source is to be energized at all times during building occupancy.
- Lighting levels on the sign face(s) should be confirmed after any change in external lighting types or levels.
- It is recommended that periodic inspections be performed in accordance with all applicable codes.
- Install this sign indoors only, where not exposed to direct sunlight, liquid spray or temperatures outside the range of +10° to 40°C.
- Cleaning of the sign face(s) with a damp cloth is recommended during monthly inspections.
- When a retrofit involves the replacement of existing electric exit signs the electric junction box must be sealed with an approved blank cover plate before the installation of our Eco Exit Sign.

ACTIVATION:

CAUTION - MINIMUM 5 FOOT-CANDLES (54 LUX) OF LED, FLUORESCENT, METAL HALIDE OR MERCURY VAPOR ILLUMINATION MUST BE PRESENT ON THE SIGN FACE AT ALL TIMES DURING BUILDING OCCUPANCY

LISTING (UL924)

SIGNS WILL REMAIN LEGIBLE FOR A MINIMUM OF 90 MINUTES (1-1/2 HOURS) AT A 15.25 METER (50 FOOT) VIEWING DISTANCE.

ASSEMBLY:

- Insert exit sign into front channel. Insert exit sign or wall mount black panel (make sure holes with tab on panel face up) into back channel. Make sure panels are securely seated in channels.
- Determine how sign is to be mounted. If ceiling or flag mounted, slide mounting bracket into outside channel before attaching final extrusion. Using one screw (8-32x5/8") position and attach mounting bracket to frame.
- Attach extrusion using two screws (6-32x3/4") to preassembled 3-sided frame (mounting holes are located inside channel near end). Make sure panels are securely seated in channels.
- Sign is ready to be installed.

INSTALLATION:

- 1.) **Ceiling or flag mounting** - determine and mark position of sign on wall or ceiling. Mount sign using (4) holes to surface or electrical box (no hardware is included for this step). Installation is now complete.
- 2.) **Wall mounting** - Determine and mark position of sign on wall. Mount bracket to wall or electrical box (no hardware is included for this step) then snap sign onto bracket. Installation is now complete.

Note: Check electrical code requirements before installing sign to any electrical box.

DIRECTIONAL INDICATORS:

MODEL NUMBER 7210-SAF-B Single sided Red EXIT with Silver Frame and Bracket

MODEL NUMBER 7210-SAF-2-B Double sided Red EXIT with Silver Frame and Bracket

MODEL NUMBER 7220-SAF-B Single sided Green EXIT with Silver Frame and Bracket

MODEL NUMBER 7220-SAF-2-B Double sided Green EXIT with Silver Frame and Bracket

- SUITABLE FOR FLOOR PROXIMITY INSTALLATION -

Jessup Manufacturing Company
tel: 815-385-6650 fax: 815-385-0079
www.jessupmfg.com

– SAVE THESE INSTRUCTIONS –
– FOR FIRE SAFETY INSPECTION –